



GX-A604

4-Channel Full Range Amplifier



Powerful and Compact 435-Watt Amplifier

A 435-watt, four-channel, full-range powerhouse, the GX-A604 – with on-board variable electronic crossovers and variable Bass EQ on the rear channels – is certainly a versatile system building tool. With all that power inside a 2-1/16" (52mm) high, 8-1/8" (206mm) wide and 11-13/16" (300mm) deep package, the GX-A604 is easy to install yet can serve as the foundation of a truly sophisticated sound system.

Features

- ▶ Cast-aluminum heat sink
- ▶ Built-in electronic crossover networks
- ▶ Bass boost circuits



Product specifications:

- ▶ Number of Channels: 4 channels
- ▶ 4-Ohm Power Output: 60W rms x 4, <1% THD+N
- ▶ 2-Ohm Power Output: 85W rms x 4, <1% THD+N
- ▶ Bridged Power Output: 170W x 2 into 4 ohms
- ▶ Total Peak Power Output: 435W
- ▶ Signal-to-Noise Ratio: 93dB (ref rated output @ 4 ohms)
- ▶ Frequency Response: 20Hz–20kHz \pm 1dB
- ▶ THD+N: <1%
- ▶ Input Sensitivity: 200mV–20V
- ▶ Variable Bass Boost: 0 to +12dB @ 45Hz
- ▶ Dimensions (L x W x H): 300mm x 206mm x 52mm (11-13/16" x 8-1/8" x 2-1/16")

What's in the box:

- 1 GX-A604 amplifier
- 1 Owner's manual